

A6E-AUD5

A6E Option Switch Settings: 1 (Pulse/ICT002U)

Supported bill AUD 5, 10, 20, 50, 100 5bills.

A6E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject \$A 5	ON											
★ Accept \$A 5	OFF											
★ Reject \$A 10		ON										
★ Accept \$A 10		OFF										
★ Reject \$A 20			ON									
★ Accept \$A 20			OFF									
★ Reject \$A 50				ON								
★ Accept \$A 50				OFF								
★ Reject \$A 100					ON							
★ Accept \$A 100					OFF							
★ Interface(VCP) Mode	(Note.3)					ON						
★ Diagnostic Mode	(Note.4)					OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / \$A 5	1 pulse / \$A 5	(Note.5)						OFF	OFF			
3 pulses / \$A 5	5 pulses / \$A 5	(Note.5)						ON	OFF			
5 pulses / \$A 5	10 pulses / \$A 5	(Note.5)						OFF	ON			
6 pulses / \$A 5	20 pulses / \$A 5	(Note.5)						ON	ON			
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Default setting(Factory configuration has all switches in the OFF position.)

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Interface(VCP) Mode is for USB connection of ICT002U.

(4) Diagnostic Mode is for USB connection of Autotest tool.

(5) Special pulse:When DIP-SW4 is ON,AUD 5=1 pulse,or 3 pulses,or 5 pulses,or 6 pulses.

Normal pulse:When DIP-SW4 is OFF,AUD 5=1 pulse,or 5 pulses,or 10 pulses,or 20 pulses.

A6E-AUD5(Pulse/ICT002U)

Remove the front cover and the dip-switch is on the CPU board.

A6E Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ICT002U Mode		OFF		
Reserved			ON	
Reserved			OFF	
★ Special pulse (Note 5)				ON
Normal pulse (Note 5)				OFF

★ Manufacture setting

A6E Interface Settings: 4 (ICT002U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON		
★ ICT002U Mode		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT002U	Pulse
BV1	\$A 5	\$A 5
BV2	\$A 10	\$A 10
BV3	\$A 20	\$A 20
BV4	\$A 50	\$A 50
BV5	\$A 100	\$A 100