

## BR2300-AMD2

### BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill AMD 1000, 2000 2bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject AMD 1000	ON									
	Accept AMD 1000	OFF									
★	Reject AMD 2000		ON								
	Accept AMD 2000		OFF								
	Reserved			ON							
★	Reserved			OFF							
	High Acceptance (Note.3)				ON						
★	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 (MDB Only)					ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode			ICT-BC Mode						
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)			Connect with MDB Connector						ON
	Decrypt MODE	Standard MDB Recycler Function			★ Connect with RS232 Connector						OFF

#### ★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2 Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: Calibration card is needed.

### Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB
BV1	AMD 1000	AMD 1000	AMD 1000
BV2	AMD 2000	AMD 2000	AMD 2000

Recycler banknote inventory	
AMD 1000	45 pcs
AMD 2000	45 pcs