

BR2300-INR7

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill INR 10, 20, 50, 100, 200, 500, 2000 7 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject INR 10 & 20 & 50 & 100	ON									
	Accept INR 10 & 20 & 50 & 100	OFF									
	Reject INR 200 & 500		ON								
★	Accept INR 200 & 500		OFF								
	Reject INR 2000			ON							
★	Accept INR 2000			OFF							
★	Medium Security (Note.3)			ON							
	High Security			OFF							
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB only)				ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal					OFF	OFF				
	Load Banknote to Recycle					ON	OFF				
	Load Banknote to Stacker					OFF	ON				
	Unload Banknote to Stacker					ON	ON				
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector				OFF	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note. 1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note. 2: Recycled Banknote represents virtual MDB coin type.

Note. 3: Medium Security mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

Note. 4: calibrate card.

BR2300-INR7 (MDB/ICT-BC/ccTalk)

Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB
BV1	INR 10	INR 10	INR 10
BV2	INR 20	INR 20	INR 20
BV3	INR 50	INR 50	INR 50
BV4	INR 100	INR 100	INR 100
BV5	INR 200	INR 200	INR 200
BV6	INR 500	INR 500	INR 500
BV7	Reserve	Reserve	Reserve
BV8	INR 2000	INR 2000	INR 2000