

BR2300-LAK8

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill LAK 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject LAK 500 & 1000 & 2000	ON									
	Accept LAK 500 & 1000 & 2000	OFF									
★	Reject LAK 5000 & 10000 & 20000		ON								
	Accept LAK 5000 & 10000 & 20000		OFF								
★	Reject LAK 50000 & 100000			ON							
	Accept LAK 50000 & 100000			OFF							
★	High Acceptance (Note.3)				ON						
	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 (MDB Only)					ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector					ON
	Decrypt MODE	Standard MDB Recycler Function				Connect with RS232 Connector					OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2 Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: calibrate card.

Currency Assign Data

Interface Bill value	MDB		ICT-BC		ccTalk	
BV1	LAK	500	LAK	500	LAK	500
BV2	LAK	1000	LAK	1000	LAK	1000
BV3	LAK	2000	LAK	2000	LAK	2000
BV4	LAK	5000	LAK	5000	LAK	5000
BV5	LAK	10000	LAK	10000	LAK	10000
BV6	LAK	20000	LAK	20000	LAK	20000
BV7	LAK	50000	LAK	50000	LAK	50000
BV8	LAK	100000	LAK	100000	LAK	100000