

BR2300-SAR4

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill SAR 1, 5, 10, 50 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject SAR 1	ON									
★	Accept SAR 1	OFF									
★	Reject SAR 5 & 10		ON								
★	Accept SAR 5 & 10		OFF								
★	Reject SAR 50			ON							
★	Accept SAR 50			OFF							
★	High Acceptance (Note.3)				ON						
★	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 (MDB Only)					ON					
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector					ON
	Decrypt MODE	Standard MDB Recycler Function				Connect with RS232 Connector					OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2 Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: Calibration card is needed.

BR2300-SAR4 (MDB/ICT-BC/ccTalk)

Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB	Recycler banknote inventory	
BV1	SAR 1	SAR 1	SAR 1	SAR 1	45 pcs
BV2	SAR 5	SAR 5	SAR 5	SAR 5	40 pcs
BV3	SAR 10	SAR 10	SAR 10	SAR 10	40 pcs
BV4					
BV5	SAR 50	SAR 50	SAR 50	SAR 50	40 pcs