

BR2300-THB5

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject THB 20 & 50 & 100	ON									
	Accept THB 20 & 50 & 100	OFF									
★	Reject THB 500		ON								
	Accept THB 500		OFF								
★	Reject THB 1000			ON							
	Accept THB 1000			OFF							
★	High Acceptance (Note.3)				ON						
	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 (MDB Only)					ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector					ON
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector					OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2 Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: calibration card is needed.

Currency Assign Data

Interface Bill value	MDB	ICT-BC	ccTalk
BV1	THB 20	THB 20	THB 20
BV2	THB 50	THB 50	THB 50
BV3	THB 100	THB 100	THB 100
BV4	THB 500	THB 500	THB 500
BV5	THB 1000	THB 1000	THB 1000