

BR2300-TWD4

BR2300 DIP SWITCHES SETTING : (MDB/ICT104R/ccTalk)

Supported bill TWD 100, 200, 500, 1000 4 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
	Reject TWD 100	ON									
★	Accept TWD 100	OFF									
	Reject TWD 200		ON								
★	Accept TWD 200		OFF								
	Reject TWD 500			ON							
★	Accept TWD 500			OFF							
	Reject TWD 1000				ON						
★	Accept TWD 1000				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2					ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT104R Mode								ON	ON	
	ccTalk	MDB Mode			ICT104R Mode						
★	Encryption MODE	Virtual MDB Recycler Function (Note.2)				Rseerved					ON
	Decrypt MODE	Standard MDB Recycler Function				Rseerved					OFF

★ Manufacture setting

After setting dip switch of the credit pulses,
you should reset the bill acceptor again.

Note. 1: Turn this dip to with restart the bill acceptor
will restore ccTalk address to its default value
of 40 and the encryption key to its default value
of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: Need calibration card.

Currency Assign Data

Interface Bill value	ccTalk	ICT104R	MDB
BV1	TWD 100	TWD 100	TWD 100
BV2	TWD 200	TWD 200	TWD 200
BV3	TWD 500	TWD 500	TWD 500
BV4	TWD 1000	TWD 1000	TWD 1000