

BR2300-UYU7

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill UYU 20, 50, 100, 200, 500, 1000, 2000 7 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject UYU 20 & 50 & 100	ON									
	Accept UYU 20 & 50 & 100	OFF									
★	Reject UYU 200 & 500		ON								
	Accept UYU 200 & 500		OFF								
★	Reject UYU 1000 & 2000			ON							
	Accept UYU 1000 & 2000			OFF							
★	High Acceptance (Note.3)				ON						
	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 (MDB Only)					ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode		ICT-BC Mode							
★	Encryption MODE	Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				Connect with RS232 Connector				OFF	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recyled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: Calibration card is needed.

Currency Assign Data

Interface Bill value	MDB	ICT-BC	ccTalk	Recycler banknote inventory	
BV1	UYU 20	UYU 20	UYU 20	UYU 20	40 pcs
BV2	UYU 50	UYU 50	UYU 50	UYU 50	40 pcs
BV3	UYU 100	UYU 100	UYU 100	UYU 100	40 pcs
BV4	UYU 200	UYU 200	UYU 200	UYU 200	40 pcs
BV5	UYU 500	UYU 500	UYU 500	UYU 500	40 pcs
BV6	UYU 1000	UYU 1000	UYU 1000	UYU 1000	40 pcs
BV7	UYU 2000	UYU 2000	UYU 2000	UYU 2000	40 pcs