

L83-EUR4

L83-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Parallel A5)

Supported bill € 5, 10, 20, 50 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / € 5	OFF	OFF	OFF							
	2 Pulses / € 5	OFF	OFF	ON							
	3 Pulses / € 5	OFF	ON	OFF							
	4 Pulses / € 5	OFF	ON	ON							
	5 Pulses / € 5	ON	OFF	OFF							
	10 Pulses / € 5	ON	OFF	ON							
	20 Pulses / € 5	ON	ON	OFF							
	100 Pulses / € 5	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept € 5				ON						
	Reject € 5				OFF						
★	Accept € 10				ON						
	Reject € 10				OFF						
★	Accept € 20				ON						
	Reject € 20				OFF						
★	Accept € 50				ON						
	Reject € 50				OFF						
★	Accept Normal				ON						
	Reject € 5(2002) & 10(2002)				OFF						

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

2 Dip Switch 1 to 5 are only for Pulse mode.

3 Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-EUR4(Pulse/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	Parallel A5 Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	CRC 16-bit checksum	ON			
	8-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	Parallel A5 Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore

CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(Parallel A5)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
★	Parallel A5 Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ccTalk	Parallel A5
BV1	€ 5	€ 5	€ 5
BV2	€ 10	€ 10	€ 10
BV3	€ 20	€ 20	€ 20
BV4	€ 50	€ 50	€ 50