

L83-EUR6

L83-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill € 5, 10, 20, 50, 100, 200 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / € 5	OFF	OFF	OFF							
2 Pulse / € 5	OFF	OFF	ON							
3 Pulse / € 5	OFF	ON	OFF							
4 Pulse / € 5	OFF	ON	ON							
5 Pulse / € 5	ON	OFF	OFF							
10 Pulse / € 5	ON	OFF	ON							
20 Pulse / € 5	ON	ON	OFF							
100 Pulse / € 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept € 5 & 10						ON				
Reject € 5 & 10						OFF				
★ Accept € 20 & 50							ON			
Reject € 20 & 50							OFF			
★ Accept € 100								ON		
Reject € 100								OFF		
★ Accept € 200									ON	
Reject € 200									OFF	
★ Normal										ON
Reject € 5(2002) & 10(2002)										OFF

★ Manufacture Default setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only for pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

L83-EUR6(Pulse/ICT104U/ccTalk)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Interface		ON	OFF	
ICT104U Interface		ON	ON	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
★ Pulse Interface		ON	OFF	
★ ICT104U Interface		ON	ON	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	CcTalk
BV1	€ 5	€ 5	€ 5
BV2	€ 10	€ 10	€ 10
BV3	€ 20	€ 20	€ 20
BV4	€ 50	€ 50	€ 50
BV5	€ 100	€ 100	€ 100
BV6	€ 200	€ 200	€ 200

Interface Settings: 2(ccTalk)

INTERFACE	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
Pulse Interface		ON	OFF	
ICT104U Interface		ON	ON	
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting