

L83-UAH9

L83/P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Smiley Parallel)

Supported bill HRYVEN 1, 2, 5, 10, 20, 50, 100, 200, 500 9bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / HRYVEN 1 & 5 (Note.3)	OFF	OFF	OFF							
	2 Pulses / HRYVEN 1 & 5 (Note.3)	OFF	OFF	ON							
	3 Pulses / HRYVEN 1 & 5 (Note.3)	OFF	ON	OFF							
	4 Pulses / HRYVEN 1 & 5 (Note.3)	OFF	ON	ON							
	5 Pulses / HRYVEN 1 & 5 (Note.3)	ON	OFF	OFF							
	10 Pulses / HRYVEN 1 & 5 (Note.3)	ON	OFF	ON							
	20 Pulses / HRYVEN 1 & 5 (Note.3)	ON	ON	OFF							
	100 Pulses / HRYVEN 1 & 5 (Note.3)	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept HRYVEN 1 & 2 (Note.3)				ON						
	Reject HRYVEN 1 & 2 (Note.3)				OFF						
★	Accept HRYVEN 5 & 10 & 20 & 50				ON						
	Reject HRYVEN 5 & 10 & 20 & 50				OFF						
★	Accept HRYVEN 100 & 200				ON						
	Reject HRYVEN 100 & 200				OFF						
★	Accept HRYVEN 500				ON						
	Reject HRYVEN 500				OFF						
★	Simulation Bill Box Has Been Removed				ON						
	Default				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Pulse Mode:

Dip 6 turn ON ,One Pulse per HRYVEN 1.

Dip 6 turn OFF,One Pulse per HRYVEN 5.

(4) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-UAH9(Pulse/ccTalk/Smiley Parallel)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	Smiley Parallel Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	CRC 16-bit checksum	ON			
	8-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	cctalk Interface		OFF	OFF	
	Smiley Parallel Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(Smiley Parallel)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	cctalk Interface		OFF	OFF	
★	Smiley Parallel Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface	Pulse		Smiley Parallel	ccTalk
	Dip 6 is ON	Dip 6 is OFF		
Bill value				
BV1	HRIVEN 1	HRIVEN 5	HRIVEN 1	HRIVEN 1
BV2	HRIVEN 2	HRIVEN 10	HRIVEN 2	HRIVEN 2
BV3	HRIVEN 5	HRIVEN 20	HRIVEN 5	HRIVEN 5
BV4	HRIVEN 10	HRIVEN 50	HRIVEN 10	HRIVEN 10
BV5	HRIVEN 20	HRIVEN 100	HRIVEN 20	HRIVEN 20
BV6	HRIVEN 50	HRIVEN 200	HRIVEN 50	HRIVEN 50
BV7	HRIVEN 100	HRIVEN 500	HRIVEN 100	HRIVEN 100
BV8	HRIVEN 200		HRIVEN 200	HRIVEN 200
BV9	HRIVEN 500		HRIVEN 500	HRIVEN 500