



GBP4

P85/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill £ 5, 10, 20, 50 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / £ 5	OFF	OFF	OFF							
2 Pulse / £ 5	OFF	OFF	ON							
3 Pulse / £ 5	OFF	ON	OFF							
4 Pulse / £ 5	OFF	ON	ON							
5 Pulse / £ 5	ON	OFF	OFF							
10 Pulse / £ 5	ON	OFF	ON							
20 Pulse / £ 5	ON	ON	OFF							
100 Pulse / £ 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept £ 5						ON				
★ Reject £ 5						OFF				
★ Accept £ 10							ON			
★ Reject £ 10							OFF			
★ Accept £ 20								ON		
★ Reject £ 20								OFF		
★ Accept £ 50									ON	
★ Reject £ 50									OFF	
High Acceptance										ON
★ High Security										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.
(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Ignore Sensor Problem(Note 1)				ON
★ Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>>> BA will be still in working order.
(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)
(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.
(The face LED will be flashing in red.)

