

V7P-QAR3

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill QAR 1, 5, 10 3bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject QAR 1 <small>(Note.4)</small>	ON											
★ Accept QAR 1 <small>(Note.4)</small>	OFF											
★ Reject QAR 5		ON										
★ Accept QAR 5		OFF										
★ Reject QAR 10			ON									
★ Accept QAR 10			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ Pulse Mode												
★ 1 pulse / QAR 1 & 5 <small>(Note.4)</small>								OFF	OFF			
5 pulses / QAR 1 & 5 <small>(Note.4)</small>								ON	OFF			
10 pulses / QAR 1 & 5 <small>(Note.4)</small>								OFF	ON			
20 pulses / QAR 1 & 5 <small>(Note.4)</small>								ON	ON			
★ Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
	60ms LO / 300ms HI									ON	OFF	
	30ms LO / 50ms HI									OFF	ON	
	150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note :

1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

4.Pulse Mode:

Dip 1 turn OFF, One Pulse per QAR 1.

Dip 1 turn ON, One Pulse per QAR 5.

V7P-QAR3(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface	Pulse	MDB	ICT104V	ICT104U
★ Bill value				
BV1	QAR 1	QAR 1	QAR 1	QAR 1
BV2	QAR 5	QAR 5	QAR 5	QAR 5
BV3	QAR 10	QAR 10	QAR 10	QAR 10

Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting