

XBA mini-PLN5

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Supported bill PLN 10, 20, 50, 100, 200 5bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject PLN 10	ON											
★	Accept PLN 10	OFF											
	Reject PLN 20		ON										
★	Accept PLN 20		OFF										
	Reject PLN 50			ON									
★	Accept PLN 50			OFF									
	Reject PLN 100				ON								
★	Accept PLN 100				OFF								
	Reject PLN 200					ON							
★	Accept PLN 200					OFF							
	Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★	Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
	Stack Banknote when Power-up						ON						
★	Reject Banknote when Power-up						OFF						
	Reserved								ON				
★	Reserved								OFF				
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
	Reserved									ON			
★	Reserved									OFF			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note : (1) Dip switches 1 to 5 are only used for pulse protocol.

(2) Calibration card is needed

XBA mini-PLN5(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / PLN 10			OFF	OFF
	5 pulses / PLN 10			OFF	ON
	10 pulses / PLN 10			ON	OFF
	25 pulses / PLN 10			ON	ON

★ Manufacture setting

Interface Bill value	JPSTD	ICT104U	ICT104V	Pulse	MDB
BV1	10	10	10	10	10
BV2		20	20	20	20
BV3		50	50	50	50
BV4		100	100	100	100
BV5		200	200	200	200

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT JPSTD converter board	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
★	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(Other)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting