

XBA mini-KZT4

XBA mini Option Switch Settings: 1(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Supported bill KZT 200, 500, 1000, 2000 4bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject KZT 200	ON											
★	Accept KZT 200	OFF											
★	Reject KZT 500		ON										
★	Accept KZT 500		OFF										
★	Reject KZT 1000			ON									
★	Accept KZT 1000			OFF									
★	Reject KZT 2000				ON								
★	Accept KZT 2000				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★	Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
★	Stack Banknote when Power-up						ON						
★	Reject Banknote when Power-up						OFF						
★	Reserved							ON					
★	Reserved							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	Reserved									ON			
★	Reserved									OFF			
★	Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

Currency Assign Data

Interface Bill value	ICT104U	RS232 A0	ccNet	Pulse	MDB	Interface Bill value	ICT104U	RS232 A0	ccNet	Pulse	MDB
BV1	KZT 200	KZT 200	KZT 200	KZT 200	KZT 200	BV4	KZT 2000	KZT 2000	KZT 2000	KZT 2000	KZT 2000
BV2	KZT 500	KZT 500	KZT 500	KZT 500	KZT 500						
BV3	KZT 1000	KZT 1000	KZT 1000	KZT 1000	KZT 1000						

XBA mini-KZT4(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / KZT 100			OFF	OFF
	2 pulses / KZT 100			OFF	ON
	5 pulses / KZT 100			ON	OFF
	20 pulses / KZT 100			ON	ON

★ Manufacture setting

Interface Settings: 2(ccNet)

	INTERFACE	SW1	SW2	SW3	SW4
★	9600 Baud Rate	ON			
	19200 Baud Rate	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	MDB Mode			OFF	OFF
★	ccNet Mode			OFF	ON
	ICT104U Mode			ON	OFF
	RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	ccNet Mode			OFF	ON
★	ICT104U Mode			ON	OFF
	RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	ccNet Mode			OFF	ON
	ICT104U Mode			ON	OFF
	RS232 A0 Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(RS232 A0)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
	MDB Mode			OFF	OFF
	ccNet Mode			OFF	ON
	ICT104U Mode			ON	OFF
★	RS232 A0 Mode			ON	ON

★ Manufacture setting

Note:(1) Dip switches 1 to 5 are only used for pulse protocol.

(2) Calibration card is needed.

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	KZT 200
3	KZT 500
4	KZT 1000
5	KZT 2000