

XBA mini-RUB8

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Supported bill P. 10, 50, 100, 200, 500, 1000, 2000, 5000 8bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject P. 10	ON											
★	Accept P. 10	OFF											
★	Reject P. 50 & 100 & 200		ON										
★	Accept P. 50 & 100 & 200		OFF										
★	Reject P. 500			ON									
★	Accept P. 500			OFF									
★	Reject P. 1000				ON								
★	Accept P. 1000				OFF								
★	Reject P. 2000 & 5000					ON							
★	Accept P. 2000 & 5000					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Stack Banknote when Power-up							ON					
★	Reject Banknote when Power-up							OFF					
★	Reserved								ON				
★	Reserved								OFF				
★	Inhibit Active High									ON			
★	Inhibit Active Low									OFF			
★	Reserved										ON		
★	Reserved										OFF		
★	Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Dip switches 1 to 5 are only used for pulse protocol.

(5) Calibration card is needed.

(6) When Dip 1 is OFF, 10 P. = 1 pulse. MDB Mode: When Dip 1 is OFF,Accept 10 P.
When Dip 1 is ON, 50 P. = 1 pulse. When Dip 1 is ON,Accept 5000 P.

Appendix

XBA mini-RUB8(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / P. 10 & 50 (Note.6)			OFF	OFF
	5 pulses / P. 10 & 50 (Note.6)			OFF	ON
	10 pulses / P. 10 & 50 (Note.6)			ON	OFF
	25 pulses / P. 10 & 50 (Note.6)			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT VCCS converter board	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
★	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(Other)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD	ICT104U	ICT104V	Pulse		MDB	
				When Dip 1 is ON	When Dip 1 is OFF	When Dip 1 is ON	When Dip 1 is OFF
BV1	P. 10	P. 10	P. 10		P. 10	P. 50	P. 10
BV2		P. 50	P. 50	P. 50	P. 50	P. 100	P. 50
BV3		P. 100	P. 100	P. 100	P. 100	P. 500	P. 100
BV4		P. 500	P. 500	P. 500	P. 500	P. 1000	P. 500
BV5		P. 1000	P. 1000	P. 1000	P. 1000	P. 5000	P. 1000
BV6		P. 5000	P. 5000	P. 5000	P. 5000	P. 200	
BV7		P. 200	P. 200	P. 200	P. 200	P. 2000	P. 200
BV8		P. 2000	P. 2000	P. 2000	P. 2000		P. 2000