

L70-COP7

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT104U/ICT104V)

Supported bill COP 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / COP 1000	OFF	OFF	OFF							
2 Pulses / COP 1000	OFF	OFF	ON							
3 Pulses / COP 1000	OFF	ON	OFF							
4 Pulses / COP 1000	OFF	ON	ON							
5 Pulses / COP 1000	ON	OFF	OFF							
10 Pulses / COP 1000	ON	OFF	ON							
20 Pulses / COP 1000	ON	ON	OFF							
100 Pulses / COP 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept COP 1000 & 2000						ON				
Reject COP 1000 & 2000						OFF				
★ Accept COP 5000							ON			
Reject COP 5000							OFF			
★ Accept COP 10000								ON		
Reject COP 10000								OFF		
★ Accept COP 20000									ON	
Reject COP 20000									OFF	
★ Accept COP 50000 & 100000										ON
Reject COP 50000 & 100000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.
 (2) Dip switches 1 to 5 are only used for pulse protocol.
 (3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L70-COP7(Pulse/ccTalk/ICT104U/ICT104V)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Interface (Restored)		OFF	ON	
ICT Interface		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Interface Bill value	ICT	Pulse	ccTalk
BV1	1000	1000	1000
BV2	2000	2000	2000
BV3	5000	5000	5000
BV4	10000	10000	10000
BV5	20000	20000	20000
BV6	50000	50000	50000
BV7	100000	100000	

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ 8-bit checksum	ON			
CRC 16-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
ICT Interface		ON	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Decrypt MODE

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Interface (Restored)		OFF	ON	
★ ICT104U Interface		ON	ON	OFF
Reserved				ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Interface (Restored)		OFF	ON	
★ ICT104V Interface		ON	ON	ON
Reserved				OFF

★ Manufacture setting