

L70-CUC7

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill CUC 1, 3, 5, 10, 20, 50, 100 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / CUC 1	OFF	OFF	OFF							
	2 Pulse / CUC 1	OFF	OFF	ON							
	3 Pulse / CUC 1	OFF	ON	OFF							
	4 Pulse / CUC 1	OFF	ON	ON							
	5 Pulse / CUC 1	ON	OFF	OFF							
	10 Pulse / CUC 1	ON	OFF	ON							
	20 Pulse / CUC 1	ON	ON	OFF							
	100 Pulse / CUC 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept CUC 1 & 3					ON					
	Reject CUC 1 & 3					OFF					
★	Accept CUC 5 & 10					ON					
	Reject CUC 5 & 10					OFF					
★	Accept CUC 20					ON					
	Reject CUC 20					OFF					
★	Accept CUC 50					ON					
	Reject CUC 50					OFF					
★	Accept CUC 100					ON					
	Reject CUC 100					OFF					

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-CUC7(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	CUC 1	CUC 1	CUC 1	CUC 1
BV2	CUC 3	CUC 3	CUC 3	CUC 3
Bv3	CUC 5	CUC 5	CUC 5	CUC 5
BV4	CUC 10	CUC 10	CUC 10	CUC 10
BV5	CUC 20	CUC 20	CUC 20	CUC 20
BV6	CUC 50	CUC 50	CUC 50	CUC 50
BV7	CUC 100	CUC 100	CUC 100	CUC 100

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting