

L70+/L70F-SAR4

L70+/L70F-P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDb)

Supported bill SAR 1, 5, 10, 50 4 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / SAR 1	OFF	OFF	OFF							
2 Pulse / SAR 1	OFF	OFF	ON							
3 Pulse / SAR 1	OFF	ON	OFF							
4 Pulse / SAR 1	OFF	ON	ON							
5 Pulse / SAR 1	ON	OFF	OFF							
10 Pulse / SAR 1	ON	OFF	ON							
20 Pulse / SAR 1	ON	ON	OFF							
100 Pulse / SAR 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept SAR 1						ON				
Reject SAR 1						OFF				
★ Accept SAR 5							ON			
Reject SAR 5							OFF			
★ Accept SAR 10								ON		
Reject SAR 10								OFF		
★ Accept SAR 50									ON	
Reject SAR 50									OFF	
★ High Security										ON
High Acceptance (Note.3)										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

L70+/L70F-SAR4(Pulse/ICT104U/ICT104V/MDb)

DIP SWITCHES SETTING : 2(Pulse)

Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

Interface Bill value	Pulse	MDb	ICT104U	ICT104V
BV1	SAR 1	SAR 1	SAR 1	SAR 1
BV2	SAR 5	SAR 5	SAR 5	SAR 5
BV3	SAR 10	SAR 10	SAR 10	SAR 10
BV4				
BV5	SAR 50	SAR 50	SAR 50	SAR 50

DIP SWITCHES SETTING : 2(ICT104U)

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting