

L70-TWD4

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill NT\$ 100, 200, 500, 1000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / NT\$ 100	OFF	OFF	OFF							
	2 Pulses / NT\$ 100	OFF	OFF	ON							
	3 Pulses / NT\$ 100	OFF	ON	OFF							
	4 Pulses / NT\$ 100	OFF	ON	ON							
	5 Pulses / NT\$ 100	ON	OFF	OFF							
	10 Pulses / NT\$ 100	ON	OFF	ON							
	20 Pulses / NT\$ 100	ON	ON	OFF							
	100 Pulses / NT\$ 100	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept NT\$ 100				ON						
	Reject NT\$ 100				OFF						
★	Accept NT\$ 200				ON						
	Reject NT\$ 200				OFF						
★	Accept NT\$ 500				ON						
	Reject NT\$ 500				OFF						
★	Accept NT\$ 1000				ON						
	Reject NT\$ 1000				OFF						
★	Reserved				ON						
	Reserved				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L70-TWD4(Pulse/ICT104U/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	ICT104U Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104	Pulse	ccTalk
BV1	100	100	100
BV2	200	200	200
BV3	500	500	500
BV4	1000	1000	1000

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	ICT104U Interface		ON	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Decrypt MODE

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	ICT104U Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting