

L70-USD6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/MDB)

Supported bill USD 1, 5, 10, 20, 50, 100 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / USD 1	OFF	OFF	OFF							
	2 Pulses / USD 1	OFF	OFF	ON							
	3 Pulses / USD 1	OFF	ON	OFF							
	4 Pulses / USD 1	OFF	ON	ON							
	5 Pulses / USD 1	ON	OFF	OFF							
	10 Pulses / USD 1	ON	OFF	ON							
	20 Pulses / USD 1	ON	ON	OFF							
	100 Pulses / USD 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept USD 1				ON						
	Reject USD 1				OFF						
★	Accept USD 5				ON						
	Reject USD 5				OFF						
★	Accept USD 10				ON						
	Reject USD 10				OFF						
★	Accept USD 20				ON						
	Reject USD 20				OFF						
★	Accept USD 50 & 100				ON						
	Reject USD 50 & 100				OFF						

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

L70-USD6(Pulse/ICT106U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U	ICT104V
BV1	USD 1	USD 1	USD 1	USD 1
BV2	USD 5		USD 5	USD 5
BV3	USD 10	USD 5	USD 10	USD 10
BV4	USD 20	USD 10	USD 20	USD 20
BV5	USD 50	USD 20	USD 50	USD 50
BV6	USD 100	USD 50	USD 100	USD 100
BV7		USD 100		

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT106U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting