

## L70+/L70F-GTQ6

### L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill GTQ 1, 5, 10, 20, 50, 100 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / GTQ 1 (DIP 6 ON) GTQ 5 (DIP 6 OFF)(Note.3)	OFF	OFF	OFF							
★ 2 Pulse / GTQ 1 (DIP 6 ON) GTQ 5 (DIP 6 OFF)(Note.3)	OFF	OFF	ON							
★ 3 Pulse / GTQ 1 (DIP 6 ON) GTQ 5 (DIP 6 OFF)(Note.3)	OFF	ON	OFF							
★ 4 Pulse / GTQ 1 (DIP 6 ON) GTQ 5 (DIP 6 OFF)(Note.3)	OFF	ON	ON							
★ 5 Pulse / GTQ 1 (DIP 6 ON) GTQ 5 (DIP 6 OFF)(Note.3)	ON	OFF	OFF							
★ 10 Pulse / GTQ 1 (DIP 6 ON) GTQ 5 (DIP 6 OFF)(Note.3)	ON	OFF	ON							
★ 20 Pulse / GTQ 1 (DIP 6 ON) GTQ 5 (DIP 6 OFF)(Note.3)	ON	ON	OFF							
★ 100 Pulse / GTQ 1 (DIP 6 ON) GTQ 5 (DIP 6 OFF)(Note.3)	ON	ON	ON							
★ Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
★ Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept GTQ 1 (Note.3)						ON				
★ Reject GTQ 1 (Note.3)						OFF				
★ Accept GTQ 5 & 10							ON			
★ Reject GTQ 5 & 10							OFF			
★ Accept GTQ 20								ON		
★ Reject GTQ 20								OFF		
★ Accept GTQ 50									ON	
★ Reject GTQ 50									OFF	
★ Accept GTQ 100										ON
★ Reject GTQ 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Pulse Mode:

Dip 6 turn ON ,One Pulse per GTQ 1.

Dip 6 turn OFF,One Pulse per GTQ 5.

## L70+/L70F-GTQ6(Pulse/ICT104U/ICT104V/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse		MDB	ICT104U	ICT104V
	DIP6 ON	DIP6 OFF			
BV1	GTQ 1		GTQ 1	GTQ 1	GTQ 1
BV2	GTQ 5	GTQ 5	GTQ 5	GTQ 5	GTQ 5
BV3	GTQ 10	GTQ 10	GTQ 10	GTQ 10	GTQ 10
BV4	GTQ 20	GTQ 20	GTQ 20	GTQ 20	GTQ 20
BV5	GTQ 50	GTQ 50	GTQ 50	GTQ 50	GTQ 50
BV6	GTQ 100	GTQ 100	GTQ 100	GTQ 100	GTQ 100

### DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting