

L70+/L70F-GTQ6

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill GTQ 1, 5, 10, 20, 50, 100 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / GTQ 1 & 5	OFF	OFF	OFF							
2 Pulse / GTQ 1 & 5	OFF	OFF	ON							
3 Pulse / GTQ 1 & 5	OFF	ON	OFF							
4 Pulse / GTQ 1 & 5	OFF	ON	ON							
5 Pulse / GTQ 1 & 5	ON	OFF	OFF							
10 Pulse / GTQ 1 & 5	ON	OFF	ON							
20 Pulse / GTQ 1 & 5	ON	ON	OFF							
100 Pulse / GTQ 1 & 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept GTQ 1 (Note.4)						ON				
Reject GTQ 1 (Note.4)						OFF				
★ Accept GTQ 5 & 10							ON			
Reject GTQ 5 & 10							OFF			
★ Accept GTQ 20								ON		
Reject GTQ 20								OFF		
★ Accept GTQ 50									ON	
Reject GTQ 50									OFF	
★ Accept GTQ 100										ON
Reject GTQ 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) Pulse Mode:

Dip 6 turn ON ,One Pulse per GTQ 1.

Dip 6 turn OFF,One Pulse per GTQ 5.

L70+/L70F-GTQ6(Pulse/ICT104U/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
ICT104U Interface		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse		ICT104U	ccTalk
	DIP 6 ON	DIP 6 OFF		
BV1	GTQ 1		GTQ 1	GTQ 1
BV2	GTQ 5	GTQ 5	GTQ 5	GTQ 5
BV3	GTQ 10	GTQ 10	GTQ 10	GTQ 10
BV4	GTQ 20	GTQ 20	GTQ 20	GTQ 20
BV5	GTQ 50	GTQ 50	GTQ 50	GTQ 50
BV6	GTQ 100	GTQ 100	GTQ 100	GTQ 100

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
ICT104U Interface		ON	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Decrypt MODE

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ ICT104U Interface		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting