

L70+/L70F-NAD9(NAD6+ZAR3)

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill NAD 10, 20, 30, 50, 100, 200 6bills.
ZAR 50, 100, 200 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / NAD10 & ZAR10	OFF	OFF	OFF							
	2 Pulses / NAD10 & ZAR10	OFF	OFF	ON							
	3 Pulses / NAD10 & ZAR10	OFF	ON	OFF							
	4 Pulses / NAD10 & ZAR10	OFF	ON	ON							
	5 Pulses / NAD10 & ZAR10	ON	OFF	OFF							
	10 Pulses / NAD10 & ZAR10	ON	OFF	ON							
	20 Pulses / NAD10 & ZAR10	ON	ON	OFF							
	100 Pulses / NAD10 & ZAR10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept NAD 10 & 20 & 30				ON						
	Reject NAD 10 & 20 & 30				OFF						
★	Accept NAD 50 & ZAR 50				ON						
	Reject NAD 50 & ZAR 50				OFF						
★	Accept NAD 100 & ZAR 100				ON						
	Reject NAD 100 & ZAR 100				OFF						
★	Accept NAD 200 & ZAR 200				ON						
	Reject NAD 200 & ZAR 200				OFF						
	Accept NAD ONLY				ON						
★	Accept NAD and ZAR				OFF						

★ Manufacture Default setting

Note 1. Please reset the bill acceptor after any changes on Dip switch.

2. Dip Switch 1 to 5 are only for Pulse mode.

3. Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L70+/L70F-NAD9(NAD6+ZAR3)(Pulse/ICT104U/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	ICT104U Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	ICT104U Interface		ON	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Pulse Mode	OFF			
	ccTalk Interface		ON	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	ICT104U Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	NAD 10	NAD 10	NAD 10
BV2	NAD 20	NAD 20	NAD 20
BV3	NAD 30	NAD 30	NAD 30
BV4	NAD 50	NAD 50	NAD 50
BV5	NAD 100	NAD 100	NAD 100
BV6	NAD 200	NAD 200	NAD 200
BV7	ZAR 50	ZAR 50	ZAR 50
BV8	ZAR 100	ZAR 100	ZAR 100
BV9	ZAR 200	ZAR 200	ZAR 200

Decrypt MODE

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF