

## L70+/L70F-PEN4

### L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT104U)

Supported bill PEN 10, 20, 50, 100 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / PEN 10	OFF	OFF	OFF							
	2 Pulses / PEN 10	OFF	OFF	ON							
	3 Pulses / PEN 10	OFF	ON	OFF							
	4 Pulses / PEN 10	OFF	ON	ON							
	5 Pulses / PEN 10	ON	OFF	OFF							
	10 Pulses / PEN 10	ON	OFF	ON							
	20 Pulses / PEN 10	ON	ON	OFF							
	100 Pulses / PEN 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept PEN 10				ON						
	Reject PEN 10				OFF						
★	Accept PEN 20				ON						
	Reject PEN 20				OFF						
★	Accept PEN 50				ON						
	Reject PEN 50				OFF						
★	Accept PEN 100				ON						
	Reject PEN 100				OFF						
★	Reserve				ON						
	Reserve				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

## L70+/L70F-PEN4(Pulse/ccTalk/ICT104U)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	ICT104U Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	10	10	10
BV2	20	20	20
BV3	50	50	50
BV4	100	100	100

### DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	ICT104U Interface		ON	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

### Decrypt MODE

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	ICT104U Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting