

P77-CHF4

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

Supported bill Sw F 10, 20, 50, 100 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★ 1 Pulse / Sw F 10	OFF	OFF	OFF								
2 Pulses / Sw F 10	OFF	OFF	ON								
3 Pulses / Sw F 10	OFF	ON	OFF								
4 Pulses / Sw F 10	OFF	ON	ON								
5 Pulses / Sw F 10	ON	OFF	OFF								
10 Pulses / Sw F 10	ON	OFF	ON								
20 Pulses / Sw F 10	ON	ON	OFF								
100 Pulses / Sw F 10	ON	ON	ON								
Fast output Pulse Lo= 50ms Hi=100ms											ON
★ Slow output Pulse Lo= 50ms Hi=300ms											OFF
Inhibit level Active Low					ON						
★ Inhibit level Active High					OFF						
★ Accept Sw F 10						ON					
Reject Sw F 10						OFF					
★ Accept Sw F 20							ON				
Reject Sw F 20							OFF				
★ Accept Sw F 50								ON			
Reject Sw F 50								OFF			
★ Accept Sw F 100									ON		
Reject Sw F 100									OFF		
Reserved										ON	
★ Reserved										OFF	

(★) Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P77-CHF4/P5(Pulse/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ccTalk Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Reserved				ON
★ Reserved				OFF

(★) Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ Encryption Mode	ON			
Decrypt Mode	OFF			
Pulse Protocol		ON		
★ ccTalk Protocol		OFF		
ccTalk Parameters Reset			ON	
★ Keep ccTalk Parameters			OFF	
Reserved				ON
★ Reserved				OFF

(★) Manufacture setting.

Note : 1.Please reset the bill acceptor after set the dip switch.

2.RS232 B1 Parameters Reset

Put this switch to on and reset power will restore the RS232 B1 address to its default value of 40 and the encryption key to its default value of 123456.

*This has to be done after finished calibration process.

Currency Assign Data

Interface Bill value	Pulse	ccTalk
BV1	10	10
BV2	20	20
BV3	50	50
BV4	100	100