

ROL7

P85 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

Supported bill Lei 1, 5, 10, 50, 100, 200, 500 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Lei 1	OFF	OFF	OFF							
2 Pulses / Lei 1	OFF	OFF	ON							
3 Pulses / Lei 1	OFF	ON	OFF							
4 Pulses / Lei 1	OFF	ON	ON							
5 Pulses / Lei 1	ON	OFF	OFF							
10 Pulses / Lei 1	ON	OFF	ON							
20 Pulses / Lei 1	ON	ON	OFF							
100 Pulses / Lei 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Lei 1						ON				
Reject Lei 1						OFF				
★ Accept Lei 5							ON			
Reject Lei 5							OFF			
★ Accept Lei 10								ON		
Reject Lei 10								OFF		
★ Accept Lei 50 & 100									ON	
Reject Lei 50 & 100									OFF	
★ Accept Lei 200 & 500										ON
Reject Lei 200 & 500										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P85-ROL7(Pulse/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ccTalk Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ccTalk	Pulse
BV1	Lei 1	Lei 1
BV2	Lei 5	Lei 5
BV3	Lei 10	Lei 10
BV4	Lei 50	Lei 50
BV5	Lei 100	Lei 100
BV6	Lei 200	Lei 200
BV7	Lei 500	Lei 500

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ Encryption MODE	ON			
Decrypt MODE	OFF			
Pulse Protocol		ON		
★ ccTalk Protocol		OFF		
ccTalk Parameters Restore Switch Please see "Note" for detail			ON	
★ Keep ccTalk Parameters			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.