

# TAO-A-USD6

## TAO-A Option Switch Settings: 1(Pulse+NISR+ICT002U+5V Enable+Out of Service)

Supported bill USD 1, 5, 10, 20, 50, 100 6 bills.

TAO-A dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject USD 1	ON											
★ Accept USD 1	OFF											
★ Reject USD 5		ON										
★ Accept USD 5		OFF										
★ Reject USD 10			ON									
★ Accept USD 10			OFF									
★ Reject USD 20				ON								
★ Accept USD 20				OFF								
★ Reject USD 50 & 100					ON							
★ Accept USD 50 & 100					OFF							
Auto Detection SEND Signal (NISR Mode only)						ON						
★ Normal High SEND Signal (NISR Mode only)						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / USD 1									OFF	OFF		
★ 2 pulse / USD 1									ON	OFF		
★ 4 pulse / USD 1									OFF	ON		
★ 20 pulse / USD 1									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Pulse mode has out of service function.

# TAO-A-USD6(Pulse+NISR+ICT002U+5V Enable+Out of Service)

## Interface Settings: 2(ICT)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ ICT002U Mode		ON	ON	
★ NISR Mode		OFF	ON	
★ Pulse Mode		ON	OFF	
★ 5V Enable Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

## Interface Settings: 2(NISR)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ ICT002U Mode		ON	ON	
★ NISR Mode		OFF	ON	
★ Pulse Mode		ON	OFF	
★ 5V Enable Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

## Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
★ Credit-Pulse Normal LOW	OFF			
★ ICT002U Mode		ON	ON	
★ NISR Mode		OFF	ON	
★ Pulse Mode		ON	OFF	
★ 5V Enable Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	ICT	NISR
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	
BV3	USD 10	USD 10	USD 5
BV4	USD 20	USD 20	USD 10
BV5	USD 50	USD 50	USD 20
BV6	USD 100	USD 100	USD 50
BV7			USD 100

## Interface Settings: 2(5V Enable)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
★ Credit-Pulse Normal LOW	OFF			
★ ICT002U Mode		ON	ON	
★ NISR Mode		OFF	ON	
★ Pulse Mode		ON	OFF	
★ 5V Enable Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting