

**TAO-A.V-AUD5**

**TAO-A.V Option Switch Settings: 1(Pulse/MDB/ccNet)**

**Supported bill \$A 5, 10, 20, 50, 100 5bills.**

TAO-V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	
★ Reject \$A 5	ON												
★ Accept \$A 5	OFF												
★ Reject \$A 10		ON											
★ Accept \$A 10		OFF											
★ Reject \$A 20			ON										
★ Accept \$A 20			OFF										
★ Reject \$A 50				ON									
★ Accept \$A 50				OFF									
★ Reject \$A 100					ON								
★ Accept \$A 100					OFF								
★ Reserved					ON								
★ Reserved					OFF								
★ <b>Pulse Moded</b>	<b>Other Moded</b>												
★ Harness Disable	BA stops working when fishing						ON						
★ Harness Enable	Normal						OFF						
★ Inhibit Active High							ON						
★ Inhibit Active Low							OFF						
★ 1 pulse / \$A 5								OFF	OFF				
★ 5 pulses / \$A 5								ON	OFF				
★ 10 pulses / \$A 5								OFF	ON				
★ 20 pulses / \$A 5								ON	ON				
★ Interface Timing Conversion	50ms LO / 50ms HI											OFF	OFF
	60ms LO / 300ms HI											ON	OFF
	30ms LO / 50ms HI											OFF	ON
	150ms LO / 150ms HI											ON	ON

★ Manufacture setting

After setting dip switch of the credit pulses,you should reset the bill acceptor again.

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

BV1=\$A 5, BV2=\$A 10, BV3=\$A 20, BV4=\$A 50, BV5=\$A 100

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

(4) CCNET DIP4 ON: BV3=\$A 5, BV4=\$A 10, BV5=\$A 20, BV6=\$A 50, BV7=\$A 100

OFF: BV1=\$A 5, BV2=\$A 10, BV3=\$A 20, BV4=\$A 50, BV5=\$A 100

**TAO-A.V-AUD5(Pulse/MDB/ccNet)**

**Interface Settings: 2(Pulse)**

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

**Interface Settings: 2(ccNet)**

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
Australian channel value mapping (Note,4)				ON
★ ICT channel value mapping				OFF

★ Manufacture setting

**TAO-V-AUD5**

**Interface Settings: 2(MDB)**

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ccNet Mode		OFF	ON	
★ MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note : (4) CCNET DIP4 ON: BV3=\$A 5, BV4=\$A 10, BV5=\$A 20, BV6=\$A 50, BV7=\$A 100  
OFF: BV1=\$A 5, BV2=\$A 10, BV3=\$A 20, BV4=\$A 50, BV5=\$A 100

**Currency Assign Data**

Interface Bill value	ccNet		Pulse	MDB
	DIP 4 ON	DIP 4 OFF		
BV1	\$A 5	\$A 5	\$A 5	\$A 5
BV2	\$A 10	\$A 10	\$A 10	\$A 10
BV3	\$A 5	\$A 20	\$A 20	\$A 20
BV4	\$A 10	\$A 50	\$A 50	\$A 50
BV5	\$A 20	\$A 100	\$A 100	\$A 100
BV6	\$A 50			
BV7	\$A 100			