

## V7-AMD2

### V7 Option Switch Settings:1(Pulse/ccTalk)

Supported bill DRAMS 1000, 2000 2bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject DRAMS 1000	ON											
★	Accept DRAMS 1000	OFF											
★	Reject DRAMS 2000		ON										
★	Accept DRAMS 2000		OFF										
★	Reserved			ON									
★	Reserved			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved					ON							
★	Reserved					OFF							
★	Reserved						ON						
★	Reserved						OFF						
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / DRAMS 1000									OFF	OFF		
★	2 pulse / DRAMS 1000									ON	OFF		
★	4 pulse / DRAMS 1000									OFF	ON		
★	20 pulse / DRAMS 1000									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

◆ Manufacture setting.

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) cctalk Parameters Restore Switch

Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

## V7-AMD2(Pulse/ccTalk)

### Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ccTalk Interface Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

### Currency Assign Data

Interface Bill value	Pulse	ccTalk
BV1	DRAMS 1000	DRAMS 1000
BV2	DRAMS 2000	DRAMS 2000

### Interface Settings: 2(ccTalk)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	ccTalk Interface Mode		OFF		
▲	ccTalk Parameters Restore Switch ( Please see Note.3 for detail) (ccTalk only)			ON	
★	Reserved			OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

▲ Note:3 cctalk Parameters Restore Switch

Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.