

V77E-IRR1

V77E Option Switch Settings : 1(Pulse/ICT/MDB)

Supported bill Rials 10000

1 bill.

V77E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Rials 10000	ON											
★ Accept Rials 10000	OFF											
★ Reserved		ON										
★ Reserved		OFF										
★ Reserved			ON									
★ Reserved			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Reserved							ON					
★ Reserved							OFF					
★ Harness Disable								ON				
★ Harness Enable								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ 1 pulse / Rials 10000									OFF	OFF		
2 pulses / Rials 10000									ON	OFF		
5 pulses / Rials 10000									OFF	ON		
20 pulses / Rials 10000									ON	ON		
★ Pulse Speed		50ms on / 50ms off								OFF	OFF	
		60ms on / 300ms off								ON	OFF	
		30ms on / 50ms off								OFF	ON	
		150ms on / 150ms off								ON	ON	

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6.SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V77E-IRR1(Pulse/ICT/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	ICT Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved				ON
★					OFF

★ Manufacture setting

Interface Settings: 3(ICT)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
★	ICT Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved				ON
★					OFF

★ Manufacture setting

Interface Settings: 4(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Interface		ON	OFF	
	ICT Interface		OFF	ON	
★	MDB Interface		ON	ON	
	Reserved				ON
★					OFF

★ Manufacture setting