

## V77E-KES3

### V77E Option Switch Settings : 1(Pulse/ICT104U/ccTalk)

Supported bill KES 50, 100, 200 3bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject KES 50	ON											
	Accept KES 50	OFF											
	Reject KES 100		ON										
★	Accept KES 100		OFF										
	Reject KES 200			ON									
★	Accept KES 200			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Harness Disable					ON							
★	Harness Enable					OFF							
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / KES 50							OFF	OFF				
	2 pulses / KES 50							ON	OFF				
	5 pulses / KES 50							OFF	ON				
	10 pulses / KES 50							ON	ON				
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) Default setting

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.  
(Please refer to "SW1" setting.)

(4) Turn this dip to with restart the bill acceptor will restore  
ccTalk address to its default value of 40 and the encryption key to its  
default value of 123456.

## V77E-KES3 (Pulse/ICT104U/ccTalk)

### Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	ICT104U Interface		OFF	ON	
	ccTalk Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	ICT104U	Pulse	ccTalk
BV1	KES 50	KES 50	KES 50
BV2	KES 100	KES 100	KES 100
BV3	KES 200	KES 200	KES 200

### Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
★	ICT104U Interface		OFF	ON	
	ccTalk Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### Interface Settings: 2(ccTalk)

	INTERFACE	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Interface		ON	OFF	
	ICT104U Interface		OFF	ON	
★	ccTalk Interface		ON	ON	
	Reserved		OFF	OFF	
★	Encryption MODE				ON
	Decrypt MODE				OFF

★ Manufacture setting