

V7E/LX7-MNT5

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/MDB/ICT104U)

Supported bill MNT 100, 500, 1000, 5000, 10000 5bills.

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MNT 100	ON											
	Accept MNT 100	OFF											
★	Reject MNT 500		ON										
★	Accept MNT 500		OFF										
★	Reject MNT 1000			ON									
★	Accept MNT 1000			OFF									
★	Reject MNT 5000				ON								
★	Accept MNT 5000				OFF								
★	Reject MNT 10000					ON							
★	Accept MNT 10000					OFF							
	Reserved					ON							
★	Reserved					OFF							
	Pulse Mode												
	Other Mode												
★	Harness Disable	BA stops working when fishing							ON				
★	Harness Enable	Normal							OFF				
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / MNT 100									OFF	OFF		
	2 pulses / MNT 100									ON	OFF		
	4 pulses / MNT 100									OFF	ON		
	20 pulses / MNT 100									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

Appendix

V7E/LX7-MNT5(Pulse/ICT104V/MDB/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	ICT104V Interface		ON	ON	
	MDB Mode		OFF	OFF	
★	Reserved				ON
					OFF

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	MNT 100	MNT 100	MNT 100	MNT 100
BV2	MNT 500	MNT 500	MNT 500	MNT 500
BV3	MNT 1000	MNT 1000	MNT 1000	MNT 1000
BV4	MNT 5000	MNT 5000	MNT 5000	MNT 5000
BV5	MNT 10000	MNT 10000	MNT 10000	MNT 10000

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	ICT104V Interface		ON	ON	
	MDB Mode		OFF	OFF	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	ICT104V Interface		ON	ON	
	MDB Mode		OFF	OFF	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	ICT104V Interface		ON	ON	
	MDB Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting