

V7E/LX7-MOP2

V7E/LX7 Option Switch Settings: 1(Pulse/ICT106U/ICT104V/M.D.B)

Supported bill BDC 10, 20
BNU 10, 20 2 bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject MOP 10	ON											
★ Accept MOP 10	OFF											
★ Reject MOP 20		ON										
★ Accept MOP 20		OFF										
★ Reserved			ON									
★ Reserved			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ High Security						ON						
★ High Acceptance						OFF						
★ Pulse Mode	Other Mode											
★ Harness Disable	BA stops working when fishing					ON						
★ Harness Enable	Normal					OFF						
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / MOP 10								OFF	OFF			
★ 5 pulses / MOP 10								ON	OFF			
★ 10 pulses / MOP 10								OFF	ON			
★ 20 pulses / MOP 10								ON	ON			
★ Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
	60ms LO / 300ms HI									ON	OFF	
	30ms LO / 50ms HI									OFF	ON	
	150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting
 (2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	MOP 10	MOP 10	MOP 10
BV2	MOP 20	MOP 20	MOP 20

V7E/LX7-MOP2(Pulse/ICT106U/ICT104V/M.D.B)

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling factor / Decimal place	100 / 2	OFF	OFF	OFF
	10 / 2	OFF	OFF	ON
	1 / 2	OFF	ON	OFF
	100 / 1	OFF	ON	ON
	10 / 1	ON	OFF	OFF
	1 / 1	ON	OFF	ON
	10 / 0	ON	ON	OFF
	1 / 0	ON	ON	ON
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT106U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON	OFF	
★ ICT106U Interface		OFF	OFF	
★ ICT104V Interface		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON	OFF	
★ ICT106U Interface		OFF	OFF	
★ ICT104V Interface		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
★ Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
★ ICT106U Interface		OFF	OFF	
★ ICT104V Interface		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON	OFF	
★ ICT106U Interface		OFF	OFF	
★ ICT104V Interface		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting