

## V7E/LX7-PEN5

### V7E/LX7 Option Switch Settings: 1(Pulse/ICT104U/RS232 A0/ccTalk)

Supported bill PEN 10, 20, 50, 100, 200 5bills.

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject PEN 10	ON											
	Accept PEN 10	OFF											
	Reject PEN 20	ON											
★	Accept PEN 20		OFF										
★	Reject PEN 50			ON									
★	Accept PEN 50			OFF									
★	Reject PEN 100				ON								
	Accept PEN 100				OFF								
	Reject PEN 200					ON							
★	Accept PEN 200					OFF							
★	Reserved						ON						
	Reserved						OFF						
	Pulse Mode	Other Mode											
★	Harness Disable	BA stops working when fishing						ON					
	Harness Enable	Normal						OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	ccTalk Parameters(default setting) (Nota.4)									ON			
	ccTalk Parameters(User setting)									OFF			
	1 pulse / PEN 10	(Nota.5)							OFF	OFF			
★	2 pulses / PEN 10	(Nota.5)							ON	OFF			
	5 pulses / PEN 10	(Nota.5)							OFF	ON			
	20 pulses / PEN 10	(Nota.5)							ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

## V7E/LX7-PEN5(Pulse/ICT104U/RS232 A0/ccTalk)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	ccTalk Interface		ON	ON	
	RS232 A0 Interface		OFF	OFF	
★	Reserved				ON
					OFF

### Currency Assign Data

Interface Bill value	ICT104U	Pulse	RS232 A0	ccTalk
BV1	PEN 10	PEN 10	PEN 10	PEN 10
BV2	PEN 20	PEN 20	PEN 20	PEN 20
BV3	PEN 50	PEN 50	PEN 50	PEN 50
BV4	PEN 100	PEN 100	PEN 100	PEN 100
BV5	PEN 200	PEN 200	PEN 200	PEN 200

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	ccTalk Interface		ON	ON	
	RS232 A0 Interface		OFF	OFF	
★	Reserved				ON
					OFF

### DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	ccTalk Interface		ON	ON	
	RS232 A0 Interface		OFF	OFF	
★	Encryption MODE				ON
	Decrypt MODE				OFF

### DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	ccTalk Interface		ON	ON	
★	RS232 A0 Interface		OFF	OFF	
★	Reserved				ON
					OFF

#### RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	PEN 10
2	PEN 20
3	PEN 50
4	PEN 100
5	PEN 200
6	Reserved
7	Reserved
8	Reserved
9	Reserved

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.