

V7E+/LX7-SAR4

V7E+/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill SAR 1, 5, 10, 50 4bills.

V7E+/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject SAR 1	ON											
★ Accept SAR 1	OFF											
★ Reject SAR 5		ON										
★ Accept SAR 5		OFF										
★ Reject SAR 10			ON									
★ Accept SAR 10			OFF									
★ Reject SAR 50				ON								
★ Accept SAR 50				OFF								
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Harness Disable						ON						
★ Harness Enable						OFF						
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / SAR 1								OFF	OFF			
5 pulses / SAR 1								ON	OFF			
10 pulses / SAR 1								OFF	ON			
20 pulses / SAR 1								ON	ON			
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E+/LX7-SAR4(Pulse/ICT104V/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	SAR 1	SAR 1	SAR 1	SAR 1
BV2	SAR 5	SAR 5	SAR 5	SAR 5
BV3	SAR 10	SAR 10	SAR 10	SAR 10
BV4				
BV5	SAR 50	SAR 50	SAR 50	SAR 50

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note 1: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

2: Remove the front cover and the dip-switch in on the CPU board.(Please refer to "Sw1" setting.)