

V7E+/LX7-TRY5

V7E+/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill TRY 5, 10, 20, 50, 100 5bills.

V7E+/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TRY 5	ON											
★ Accept TRY 5	OFF											
★ Reject TRY 10		ON										
★ Accept TRY 10		OFF										
★ Reject TRY 20			ON									
★ Accept TRY 20			OFF									
★ Reject TRY 50				ON								
★ Accept TRY 50				OFF								
★ Reject TRY 100					ON							
★ Accept TRY 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Pulse Mode	Other Mode											
★ Harness Disable	BA stops working when fishing						ON					
★ Harness Enable	Normal						OFF					
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / TRY 5								OFF	OFF			
★ 5 pulses / TRY 5								ON	OFF			
★ 10 pulses / TRY 5								OFF	ON			
★ 20 pulses / TRY 5								ON	ON			
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note.1: Default setting

Note.2: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

V7E+/LX7-TRY5(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ICT104U	ICT104V
BV1	TRY 5	TRY 5	TRY 5	TRY 5
BV2	TRY 10	TRY 10	TRY 10	TRY 10
BV3	TRY 20	TRY 20	TRY 20	TRY 20
BV4	TRY 50	TRY 50	TRY 50	TRY 50
BV5	TRY 100	TRY 100	TRY 100	TRY 100

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Note 1. Default setting

2. Use both 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3. Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)