

TRY6

L77&L77F DIP SWITCHES SETTING : 1(Pulse/RS232 A0/CCTalk)

Supported bill Lira 5, 10, 20, 50, 100, 200 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Lira 5	OFF	OFF	OFF							
2 Pulse / Lira 5	OFF	OFF	ON							
3 Pulse / Lira 5	OFF	ON	OFF							
4 Pulse / Lira 5	OFF	ON	ON							
5 Pulse / Lira 5	ON	OFF	OFF							
10 Pulse / Lira 5	ON	OFF	ON							
20 Pulse / Lira 5	ON	ON	OFF							
100 Pulse / Lira 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept Lira 5 & 10						ON				
★ Reject Lira 5 & 10						OFF				
★ Accept Lira 20							ON			
★ Reject Lira 20							OFF			
★ Accept Lira 50								ON		
★ Reject Lira 50								OFF		
★ Accept Lira 100									ON	
★ Reject Lira 100									OFF	
★ Accept Lira 200										ON
★ Reject Lira 200										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switch 1 to 5 are only for Pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L77&L77F-TRY6(Pulse/RS232 A0/CCTalk)

DIP SWITCHES SETTING : 2(Pulse)

Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	Pulse	RS232 A0	CCTalk
BV1	Lira 5	Lira 5	Lira 5
BV2	Lira 10	Lira 10	Lira 10
BV3	Lira 20	Lira 20	Lira 20
BV4	Lira 50	Lira 50	Lira 50
BV5	Lira 100	Lira 100	Lira 100
BV6	Lira 200	Lira 200	Lira 200

DIP SWITCHES SETTING : 2(CCTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
★ CCTalk Interface		OFF	OFF	
CCTalk Parameters Restore Switch Please see Note.3 for Detail		OFF	ON	
★ Encryption Mode				ON
★ Decrypt Mode				OFF

★ Manufacture setting

Note: 1.Please reset the bill acceptor after any changes on Dip switch.

2.Dip Switch 1 to 5 are only for Pulse mode.

3.Turn this dip to with restart the bill acceptor will restore

CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ RS232 A0 Mode	OFF	ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	Lira 5
4	Lira 10
5	Lira 20
6	Lira 50
7	Lira 100
8	Lira 200