

L77F/PL77-RUB7

L77F/PL77 Option Switch Settings : 1(Pulse/ICT104U/MDB/ccTalk)

Supported bill RUB 50, 100, 200, 500, 1000, 2000, 5000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / RUB 50	OFF	OFF	OFF							
	2 Pulses / RUB 50	OFF	OFF	ON							
	3 Pulses / RUB 50	OFF	ON	OFF							
	4 Pulses / RUB 50	OFF	ON	ON							
	5 Pulses / RUB 50	ON	OFF	OFF							
	10 Pulses / RUB 50	ON	OFF	ON							
	20 Pulses / RUB 50	ON	ON	OFF							
	100 Pulses / RUB 50	ON	ON	ON							
		Fast output Pulse Lo= 50ms Hi=100ms				ON					
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept RUB 50 & 100						ON				
	Reject RUB 50 & 100						OFF				
★	Accept RUB 200							ON			
	Reject RUB 200							OFF			
★	Accept RUB 500 & 1000								ON		
	Reject RUB 500 & 1000								OFF		
★	Accept RUB 2000									ON	
	Reject RUB 2000									OFF	
★	Accept RUB 5000										ON
	Reject RUB 5000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip Switch 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L77F/PL77-RUB7(Pulse/ICT104U/MDB/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	MDB Mode		ON	ON	OFF
★	Pulse Mode		ON	OFF	OFF
	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	MDB Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
★	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP)= 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP)= 0	OFF			
★	MDB Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Nota.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ccTalk	ICT104U	Pulse	MDB
BV1				
BV2	RUB 50	RUB 50	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 1000	RUB 1000
BV6	RUB 5000	RUB 5000	RUB 5000	RUB 5000
BV7	RUB 200	RUB 200	RUB 200	RUB 200
BV8	RUB 2000	RUB 2000	RUB 2000	RUB 2000