

# V7P-FJD4

## V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

### Supported bill FJD 5, 7, 10, 20 4bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject FJD 5	ON											
★ Accept FJD 5	OFF											
★ Reject FJD 7		ON										
★ Accept FJD 7		OFF										
★ Reject FJD 10			ON									
★ Accept FJD 10			OFF									
★ Reject FJD 20				ON								
★ Accept FJD 20				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ <b>Pulse Mode</b>												
★ 1 pulse / FJD 1								OFF	OFF			
★ 2 pulses / FJD 1								ON	OFF			
★ 5 pulses / FJD 1								OFF	ON			
★ 10 pulses / FJD 1								ON	ON			
★ Interface Timing Conversion		50ms LO / 50ms HI								OFF	OFF	
		60ms LO / 300ms HI								ON	OFF	
		30ms LO / 50ms HI								OFF	ON	
		150ms LO / 150ms HI								ON	ON	

★ Manufacture setting

Note :

- 1.Default setting.
- 2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.
- 3.Remove the front cover and the dip-switch in on the CPU board.
- 4.Calibrate card is needed.

# V7P-FJD4(Pulse/ICT104V/ICT104U/MDB)

## Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface	Pulse	MDB	ICT104V	ICT104U
★ Bill value				
BV1	FJD 5	FJD 5	FJD 5	FJD 5
BV2	FJD 7	FJD 7	FJD 7	FJD 7
BV3	FJD 10	FJD 10	FJD 10	FJD 10
BV4	FJD 20	FJD 20	FJD 20	FJD 20

## Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

## Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

## Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting