

# XBA mini-BYN6

## XBA mini Option Switch Settings: 1(Pulse/MDB/ccNet/RS232 A0/ICT104U)

Supported bill BYN 5, 10, 20, 50, 100, 200 6bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject BYN 5 & 10	ON											
★ Accept BYN 5 & 10	OFF											
★ Reject BYN 20		ON										
★ Accept BYN 20		OFF										
★ Reject BYN 50			ON									
★ Accept BYN 50			OFF									
★ Reject BYN 100				ON								
★ Accept BYN 100				OFF								
★ Reject BYN 200					ON							
★ Accept BYN 200					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ Reserved								ON				
★ Reserved								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ Reserved										ON		
★ Reserved										OFF		
★ Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

### Currency Assign Data

Interface Bill value	ccNet	RS232 A0	Pulse	MDB	ICT104U	Interface Bill value	ccNet	RS232 A0	Pulse	MDB	ICT104U
BV1	BYN 5	BYN 5	BYN 5	BYN 5	BYN 5	BV4	BYN 50	BYN 50	BYN 50	BYN 50	BYN 50
BV2	BYN 10	BYN 10	BYN 10	BYN 10	BYN 10	BV5	BYN 100	BYN 100	BYN 100	BYN 100	BYN 100
BV3	BYN 20	BYN 20	BYN 20	BYN 20	BYN 20	BV6	BYN 200	BYN 200	BYN 200	BYN 200	BYN 200

# XBA mini-BYN6(Pulse/MDB/ccNet/RS232 A0/ICT104U)

## Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ 1 pulse / BYN 5			OFF	OFF
5 pulses / BYN 5			OFF	ON
10 pulses / BYN 5			ON	OFF
50 pulses / BYN 5			ON	ON

★ Manufacture setting

## Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
★ 9600 Baud Rate	ON			
19200 Baud Rate	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
★ ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(RS232 A0)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
ccNet Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ RS232 A0 Mode			ON	ON

★ Manufacture setting

### RS232 A0 INFORMATION

BillType Data	
Code	Denomination
2	BYN 5
3	BYN 10
4	BYN 20
5	BYN 50
6	BYN 100
7	BYN 200

Nota:(1) Dip switches 1 to 5 are only used for pulse protocol.

(2) Calibration card is needed.