

XBA mini-AZN5

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Supported bill AZN 1, 5, 10, 20, 50 5bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject AZN 1	ON											
★ Accept AZN 1	OFF											
★ Reject AZN 5		ON										
★ Accept AZN 5		OFF										
★ Reject AZN 10			ON									
★ Accept AZN 10			OFF									
★ Reject AZN 20				ON								
★ Accept AZN 20				OFF								
★ Reject AZN 50					ON							
★ Accept AZN 50					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ Reserved								ON				
★ Reserved								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ Reserved									ON			
★ Reserved									OFF			
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Calibration card is needed.

XBA mini-AZN5(Pulse/MDB/JPSTD/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
1 pulse / AZN 1			OFF	OFF
5 pulses / AZN 1			OFF	ON
10 pulses / AZN 1			ON	OFF
25 pulses / AZN 1			ON	ON

★ Manufacture setting.

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
MDB Mode			OFF	OFF
JPSTD Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Connect with coin changer	ON			
Connect with ICT JPSTD converter board	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
MDB Mode			OFF	OFF
JPSTD Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
JPSTD Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface	ICT104U	ICT104V	JPSTD	Pulse	MDB
★ Bill value					
BV1	AZN 1	AZN 1	AZN 1	AZN 1	AZN 1
BV2	AZN 5	AZN 5		AZN 5	AZN 5
BV3	AZN 10	AZN 10		AZN 10	AZN 10
BV4	AZN 20	AZN 20		AZN 20	AZN 20
BV5	AZN 50	AZN 50		AZN 50	AZN 50