

A7/V7-BAM3

A7/V7 Option Switch Settings:1(Pulse/ccTalk)

Supported bill MARAKA 10, 20, 50 3bills.

A7/V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject MARAKA 10	ON											
★ Accept MARAKA 10	OFF											
★ Reject MARAKA 20		ON										
★ Accept MARAKA 20		OFF										
★ Reject MARAKA 50			ON									
★ Accept MARAKA 50			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / MARAKA 10									OFF	OFF		
5 pulses / MARAKA 10									ON	OFF		
10 pulses / MARAKA 10									OFF	ON		
20 pulses /MARAKA 10									ON	ON		
★ Pulse Speed	50ms on / 50ms off										OFF	OFF
	60ms on / 300ms off										ON	OFF
	30ms on / 50ms off										OFF	ON
	150ms on / 150ms off										ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-BAM3

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ccTalk Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
★ Reserved				OFF

★ Manufacture setting

Interface Settings: 3(ccTalk)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON		
★ ccTalk Interface		OFF		
cctalk Parameters Restore Switch			ON	
★ Reserved			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

▲ Put this switch to on and reset power will restore the cctalk address to its default value of 40,and the encryption key to its default value of 123456. This needs to be done after each White card Calibration.