

PHP6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT)

Supported bill ₱ 20, 50, 100, 200, 500, 1000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / ₱ 10	OFF	OFF	OFF							
2 Pulses / ₱ 10	OFF	OFF	ON							
3 Pulses / ₱ 10	OFF	ON	OFF							
4 Pulses / ₱ 10	OFF	ON	ON							
5 Pulses / ₱ 10	ON	OFF	OFF							
10 Pulses / ₱ 10	ON	OFF	ON							
20 Pulses / ₱ 10	ON	ON	OFF							
100 Pulses / ₱ 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept ₱ 20						ON				
Reject ₱ 20						OFF				
★ Accept ₱ 50							ON			
Reject ₱ 50							OFF			
★ Accept ₱ 100&200								ON		
Reject ₱ 100&200								OFF		
★ Accept ₱ 500									ON	
Reject ₱ 500									OFF	
★ Accept ₱ 1000										ON
Reject ₱ 1000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L70-PHP6(Pulse/ccTalk/ICT)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	CcTalk
BV1	20	20	20
BV2	50	50	50
BV3	100	100	100
BV4	500	200	200
BV5	1000	500	500
BV6	200	1000	1000

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ Encryption Mode				ON
★ Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Decrypt MODE

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ ICT104V Mode		ON	ON	ON

★ Manufacture setting

ICT Credit: 20P->0x40 , 50P->0x41 , 100P->0x42 , 500P->0x43 , 1000P->0x44 , 200P->0x45

DIP SWITCHES SETTING : 2(ICT104)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ ICT104 Mode		ON	ON	OFF