

# L70/L70F-CAD5

## L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill CAD 5, 10, 20, 50, 100 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / CAD 5	OFF	OFF	OFF							
2 Pulses / CAD 5	OFF	OFF	ON							
3 Pulses / CAD 5	OFF	ON	OFF							
4 Pulses / CAD 5	OFF	ON	ON							
5 Pulses / CAD 5	ON	OFF	OFF							
10 Pulses / CAD 5	ON	OFF	ON							
20 Pulses / CAD 5	ON	ON	OFF							
100 Pulses / CAD 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept CAD 5						ON				
Reject CAD 5						OFF				
★ Accept CAD 10							ON			
Reject CAD 10							OFF			
★ Accept CAD 20								ON		
Reject CAD 20								OFF		
★ Accept CAD 50									ON	
Reject CAD 50									OFF	
★ Accept CAD 100										ON
Reject CAD 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.  
(2) Dip switches 1 to 5 are only used for pulse protocol.

# L70/L70F-CAD5(Pulse/ICT104U/ICT104V/MDB)

## DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	CAD 5	CAD 5	CAD 5	CAD 5
BV2	CAD 10	CAD 10	CAD 10	CAD 10
BV3	CAD 20	CAD 20	CAD 20	CAD 20
BV4	CAD 50	CAD 50	CAD 50	CAD 50
BV5	CAD 100	CAD 100	CAD 100	CAD 100

## DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting