

L70/L70F-XCD5

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/ MDB)

Supported bill XCD 5, 10, 20, 50, 100 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / XCD 5	OFF	OFF	OFF							
2 Pulses / XCD 5	OFF	OFF	ON							
3 Pulses / XCD 5	OFF	ON	OFF							
4 Pulses / XCD 5	OFF	ON	ON							
5 Pulses / XCD 5	ON	OFF	OFF							
10 Pulses / XCD 5	ON	OFF	ON							
20 Pulses / XCD 5	ON	ON	OFF							
100 Pulses / XCD 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept XCD 5						ON				
Reject XCD 5						OFF				
★ Accept XCD 10							ON			
Reject XCD 10							OFF			
★ Accept XCD 20								ON		
Reject XCD 20								OFF		
★ Accept XCD 50									ON	
Reject XCD 50									OFF	
★ Accept XCD 100										ON
Reject XCD 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L70/L70F-XCD5(Pulse/ICT104U/ICT104V/ MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	XCD 5	XCD 5	XCD 5	XCD 5
BV2	XCD 10	XCD 10	XCD 10	XCD 10
BV3	XCD 20	XCD 20	XCD 20	XCD 20
BV4	XCD 50	XCD 50	XCD 50	XCD 50
BV5	XCD 100	XCD 100	XCD 100	XCD 100

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting