

L70U-COP7

L70U/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/ccTalk)

Supported bill COP 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

★	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / COP 1000	OFF	OFF	OFF							
	2 Pulses / COP 1000	OFF	OFF	ON							
	3 Pulses / COP 1000	OFF	ON	OFF							
	4 Pulses / COP 1000	OFF	ON	ON							
	5 Pulses / COP 1000	ON	OFF	OFF							
	10 Pulses / COP 1000	ON	OFF	ON							
	20 Pulses / COP 1000	ON	ON	OFF							
	100 Pulses / COP 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept COP 1000 & 2000						ON				
	Reject COP 1000 & 2000						OFF				
★	Accept COP 5000							ON			
	Reject COP 5000							OFF			
★	Accept COP 10000								ON		
	Reject COP 10000								OFF		
★	Accept COP 20000									ON	
	Reject COP 20000									OFF	
★	Accept COP 50000 & 100000										ON
	Reject COP 50000 & 100000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L70U-COP7(Pulse/ICT104U/ICT104V/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT Interface		ON	ON	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON	OFF	
	ICT Interface		ON	ON	
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Encryption MODE				ON
	Decrypt MODE				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	ICT104U Mode		ON	ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	ICT104V Mode		ON	ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ICT104V	ccTalk
BV1	COP 1000	COP 1000	COP 1000	COP 1000
BV2	COP 2000	COP 2000	COP 2000	COP 2000
BV3	COP 5000	COP 5000	COP 5000	COP 5000
BV4	COP 10000	COP 10000	COP 10000	COP 10000
BV5	COP 20000	COP 20000	COP 20000	COP 20000
BV6	COP 50000	COP 50000	COP 50000	COP 50000
BV7	COP 100000	COP 100000	COP 100000	