

V7E/LX7-FJD6

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill FJD 5, 7, 10, 20, 50, 100 6bill

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject FJD 5	ON											
★	Accept FJD 5	OFF											
★	Reject FJD 7		ON										
★	Accept FJD 7		OFF										
★	Reject FJD 10			ON									
★	Accept FJD 10			OFF									
★	Reject FJD 20				ON								
★	Accept FJD 20				OFF								
★	Reject FJD 50					ON							
★	Accept FJD 50					OFF							
★	Reject FJD 100						ON						
★	Accept FJD 100						OFF						
	Pulse Mode	Other Mode											
★	Harness Disable	BA stopped working when fishing						ON					
★	Harness Enable	Normal						OFF					
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / FJD 1							OFF	OFF				
★	2 pulses / FJD 1							ON	OFF				
★	5 pulses / FJD 1							OFF	ON				
★	10 pulses / FJD 1							ON	ON				
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.
(2) Dip Switch 1 to 5 are only for Pulse mode.

V7E/LX7-FJD6(Pulse/ICT104V/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1	FJD 5	FJD 5	FJD 5	FJD 5
BV2	FJD 7	FJD 7	FJD 7	FJD 7
BV3	FJD 10	FJD 10	FJD 10	FJD 10
BV4	FJD 20	FJD 20	FJD 20	FJD 20
BV5	FJD 50	FJD 50	FJD 50	FJD 50
BV6	FJD 100	FJD 100	FJD 100	FJD 100

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
★	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
	ICT104V Interface		OFF	ON	
★	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting