

V7E+/LX7-SAR5

V7E+/LX7 Option Switch Settings: 1 (Pulse/ICT106U/MDB)

Supported bill SAR 1, 5, 10, 50, 100 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject SAR 1	ON											
	Accept SAR 1	OFF											
★	Reject SAR 5		ON										
★	Accept SAR 5		OFF										
	Reject SAR 10			ON									
★	Accept SAR 10			OFF									
	Reject SAR 50				ON								
★	Accept SAR 50				OFF								
	Reject SAR 100					ON							
★	Accept SAR 100					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing					ON						
★	Harness Enable	Normal					OFF						
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / SAR 1								OFF	OFF			
	5 pulses / SAR 1								ON	OFF			
	10 pulses / SAR 1								OFF	ON			
	20 pulses / SAR 1								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7E+/LX7-SAR5(Pulse/ICT106U/MDB)

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION		SW1	SW2	SW3	SW4
★	Scaling factor(SF) / Decimal Point Position (DPP)	100 / 2	OFF	OFF	OFF	
		10 / 2	OFF	OFF	ON	
		1 / 2	OFF	ON	OFF	
		100 / 1	OFF	ON	ON	
		10 / 1	ON	OFF	OFF	
		1 / 1	ON	OFF	ON	
		10 / 0	ON	ON	OFF	
		1 / 0	ON	ON	ON	
	Reserved					ON
★	Reserved					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse mode		ON	OFF	
	ICT106U mode		OFF	ON	
	MDB mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse mode		ON	OFF	
	ICT106U mode		OFF	ON	
★	MDB mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT106U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse mode		ON	OFF	
★	ICT106U mode		OFF	ON	
	MDB mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U
BV1	SAR 1	SAR 1	SAR 1
BV2	SAR 5	SAR 5	SAR 5
BV3	SAR 10	SAR 10	SAR 10
BV4			
BV5	SAR 50	SAR 50	SAR 50
BV6	SAR 100	SAR 100	SAR 100