

V7E+/LX7-SRD5

V7E+/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill SRD 5, 10, 20, 50, 100 5bills.

V7E+/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject SRD 5	ON											
★ Accept SRD 5	OFF											
★ Reject SRD 10		ON										
★ Accept SRD 10		OFF										
★ Reject SRD 20			ON									
★ Accept SRD 20			OFF									
★ Reject SRD 50				ON								
★ Accept SRD 50				OFF								
★ Reject SRD 100					ON							
★ Accept SRD 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
Pulse Mode	Other Mode											
★ Harness Disable	BA stops working when fishing						ON					
★ Harness Enable	Normal						OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / SRD 5									OFF	OFF		
★ 2 pulses / SRD 5									ON	OFF		
★ 4 pulses / SRD 5									OFF	ON		
★ 5 pulses / SRD 5									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

★ Manufacture setting

V7E+/LX7-SRD5(Pulse/ICT104V/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
ICT104U Interface		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
ICT104U Interface		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
ICT104U Interface		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

Note 1. Default setting.

2. Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.
3. Remove the front cover and the dip-switch in on the CPU board.

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1				
BV2	SRD 5	SRD 5	SRD 5	SRD 5
BV3	SRD 10	SRD 10	SRD 10	SRD 10
BV4	SRD 20	SRD 20	SRD 20	SRD 20
BV5	SRD 100	SRD 100	SRD 100	SRD 100
BV6	SRD 50	SRD 50	SRD 50	SRD 50

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting